

CM-P1

Fire Alarm Control Panel

ISO9001

Approvals: CE



■ ADVANTAGES

- * Zone range is from 5 to 100 zones
- * 2 stages accumulation function to prevent from false alarms
- * With no voltage output contacts and voltage contacts
- * The unit also can combine with our broadcast host and emergency telephone into 3-in-1 system for multipurpose

■ EXTERNAL DIMENSIONS

MODEL	Wall Mounting Type					
CIRCUIT NO.	5L - 10L	15L	20L	25L - 30L	35L - 40L	45L - 50L
H (mm)	400	495	580	520	580	700
W (mm)	300	300	300	480	480	480
D (mm)	120	120	120	180	180	180

Other circuit and dimensions can be order.

■ SPECIFICATION

MODEL NO.	CM-P1	CURRENT VOLTAGE	24V DC operation voltage, below 5V 32mA
POWER SUPPLY	230V AC 50/60Hz	CHARGING CURRENT	26V DC, under 450mA, Trickle Charge
STAND-BY BATTERY	24V DC	DETECTORS	No limit of R.O.R. Heat or Fixed Temp. Heat detect can be installed; each circuit can connect to a maximum of 20 smoke detectors (standby current for detector: 24V DC 25μA below)
EOL RESISTOR	10KΩ		NO. OF INDICATORS
EXTERNAL CIRCUIT RESISTANCE	To-and-fro below 50 Ω	CASE MATERIAL	1.2 mm - 2.0mm Steel plate with powder coating
NO. OF BELLS	1.2 times of panel circuits	REPORT CONTACT	No voltage N.O. contact Capacity 250V AC 7A × 2 sets
MAIN AUDIO	Single-tone buzzer, above 85dB		

■ ORDER INFORMATION

CM-P1	FACP with battery	SPARE MODEL NO.
OPTION MODEL NO.		
-T	Optional Telephone 1 set	
-A	Optional no voltage contacts (5 ZONES as 1 unit)	YFP-T4(5 ZONES as 1 unit)
-B	Optional voltage contacts (5 ZONES as 1 unit)	YFP-T3(5 ZONES as 1 unit)
-C	Optional annunciator output (It need to be ordered when it's connected to Annunciator Panel : 5 ZONES as 1 unit)	YFP-T8(A): (5 ZONES as 1 unit)
		YFP-T8(B): (10 ZONES as 1 unit)
-D	Optional ZONE BELL (5 ZONES as 1 unit)	YFP-T3(5 ZONES as 1 unit)
		YFP-D1(5 ZONES as 1 unit)