

# Wall Mount Mini Sirine

## SI-MS-01



### Application

The SI-MS-01 is designed to provide both audible and visible alarm in case of abnormalities. It can work in conditions where DC voltage may fluctuate which are capable to produce 110db sound pressures. The reliability has been achieved through simple design. Anti tamper switch provides additional level of protection a solid protection after commissioned.

### Spesification

|                  |                                      |
|------------------|--------------------------------------|
| Model Available  | : SI-MS-01 (Wall Mount Mini Sirine). |
| Dimension        | : 125(L) x 73(W) x 45(H) mm          |
| Input Voltage    | : 12V DC.                            |
| Rated Current    | : 300mA.                             |
| Rated Voltage    | : 103 db/min.                        |
| Flashes          | : 150/min.                           |
| Purpose          | : Security alarm.                    |
| Installation     | : Flush or Surface.                  |
| Electrical Spec. | : 1W, 12V, 0.3A.                     |
| Wire Connections | : 22AWG, 350mm.                      |
| Design           | : Simple and clear for operation.    |