



## Fire Manual Station / Call Point MCP-718

ISO 9001, CE Approved

### Description :

This Fire Manual Station are for indoor use and are part of full range of plastic call point and accessories.

This Fire Manual Station can quickly transmit a signal to the fire receiver terminals or the repeaters while the button under a transparent protective cover has been pushed at the first finding of a fire accident. (This signal is beyond the accumulated time limitation).

There is a light over the button. The light will light up as a signal has been exactly received by the receiver terminal.

There is a telephone jack for a telephone communication with attendant at the fire receiver terminal.



### Advantages :

1. Auto-Return by pushing button, no need to disassemble the main body.
2. Response light available to identify the operation completed.
3. Reinforced transparent protective cover is reusable.
4. All plastic are fire-proof, light, convenient and stylish.
5. Outside cord distribution with terminators to easy on work

### Specifications:

Model	MCP-718
Rated Voltage	DC 24V
Rated Current	75 mA
Additional Feature	Telephone Plug/ Indification Lamp
Ambient Temperature	0 - 55 °C
Relative Humidity	10 - 95 %RH
Dimensions	∅ 140 x 46 mm
Color	Red
Weight	155 g

